



KODAK VIDEO MONITOR CFH-S10



The KODAK Video Monitor CFH-S10 brings you closer to the people, places, and pets that you care about—no matter where you are. Check in on loved ones with smooth HD streaming video, crisp two-way audio, and automatic night vision using the free iSecurity+ app (iOS, Android). Equipped with motion detection, the KODAK Video Monitor CFH-S10 automatically records and stores video clips in the cloud for last 24 hours* and sends mobile notifications to your smartphone or tablet so you know what's going on (premium storage and smart detection plans available for purchase). Internal antenna expands your existing home network coverage, and integration with the IFTTT (If This Then That) iSecurity+ Channel lets you connect the KODAK Video Monitor CFH-S10 WiFi camera with other devices or apps for more automation. With the KODAK Video Monitor CFH-S10, you'll always stay close to home.



HD Video Quality




Lifetime 24-Hour Cloud Storage



Night Vision



Extensive Field of View



2-Way Audio Talkback



Wireless Connectivity

* FREE 7-Day Cloud Storage for 1st year. Look back on motion-triggered events captured and recorded with FREE 7-Day Cloud Storage for the first year (FREE Lifetime 24-Hour Cloud Storage after the first year).

GREATER PEACE OF MIND

Playback recorded motion-triggered video clips—store in the cloud—from the last 24 hours*. Now all KODAK S-Series cameras include Lifetime 24-Hour Cloud Storage so you can rest assured that you'll never miss a moment.

SMARTER PLANS

Enjoy optional Smart Detection, 14-Day or 30-Day Cloud Storage with Smart Detection plans for your KODAK S-Series camera. Smart Detection uniquely integrates computer vision technology to filter alerts by "People" or "Activity" to reduce false alarms by up to 98%.

EXPANDED AUTOMATION

Connect any KODAK S-Series camera to the IFTTT (If This Then That) iSecurity+ Channel (ifttt.com/isecurityplus) for added functionality and features with other devices or apps. Dozens of iSecurity+ "IF" and "DO" recipes let you set automatic triggers or actions—such as enabling or disabling motion detection based on GPS location, or aiming your camera in a new direction.

KODAK VIDEO MONITOR CFH-S10

Product Specifications	
Network Interface	802.11b/g/n WLAN
Antenna	Internal
Network Security	WEP (40-bit, 128-bit)/WPA (TKIP, AES)/WPA2 (TKIP, AES)
RF/Wireless	ISM Band 2.4 GHz
Image Sensor	2MP 1/3 Inch CMOS Sensor
Lens	Focal Length: 3.85mm, F2.2
Viewing Angle	Horizontal: 92°, Vertical: 49°, Diagonal: 109°
IR Operating Mode	Always OFF, Always ON or AUTO
Infrared (IR)Night Vision	Four Medium Power IR LEDs, 850nm 6 meter Illumination Distance
IR Cut-off Filter	Dual Mode Switching for DAY/NIGHT Viewing
Auto IR Mode (Enabled)	Turns ON When Ambient Light is 3 + 2 LUX or Less
Auto IR Mode (Disabled)	Turns OFF When Ambient Light is 6 + 3 LUX or Greater
Ambient Light Sensor	RoHS Compliant 560nm Luminance Detector
Video Codecs	H.264
Resolution	Dual stream: 1280x720, 640x352, 320x176
Frame Rate	Up to 30 Frames Per Second
Still Image Capture	720p Still Capture
ePTZ	Yes, 2x Digital Zoom
Audio Codecs	G.711, AAC, PCM
Audio IN	Built-in Microphone, -38dB +2dB
Audio Out	Yes, built-in speaker
Buttons	Factory Reset
Switches	Quick Set-up Mode
Power	External AC-to-DC Switching Power Adapter INPUT: 100-240V AC, 50/60Hz, Output: 5V DC, 1.0A
Operations Environment	Temperature: 32°F — 104°F (0°C to 40°C), Humidity: 0-90%



PACKAGE CONTENTS

- Power Adapter
- Camera Base
- Mounting Kit
- Quick Installation Guide

TENDINSIGHTS.COM

Tend, 46567 Fremont Boulevard, Fremont, CA 94538
© 2017 Tend Insights, Inc.
The Kodak trademark, logo and trade dress are used under license from Kodak.
All information contained in this document is subject to change without notice.

